













General Purpose AC Servo Drives

## **EL7-RS Series**

EL7-RS Series AC Servo Product is a whole new midrange AC servo drivers and motors product range that we have proudly developed at Leadshine Technology Co.,Ltd. This product series provides more in demanded functionalities and control. While designing this AC servo drive series with cost concerns in mind, this product series doesn't compromise in term of performance and functions.

EL7-RS Series AC Servo Drive comes with power rating from 400W up to 7500W which supports Modbus communication protocol in addition to analogue and pulse + direction input control. Using RS485 protocol, multi axis network of EL7-RS series servo drive can be realized and controlled from 1 single master device.







Fiber laser



Electronics




Semiconductor





### Frequency response

Quicker system response of 3.2kHz for higher precision




### Advanced servo computing

One-Click Tuning - Follow a few easy steps to get servo tuning done. Gain adjustments will be automatically set, shortening tuning time.


End vibration suppression for flexible structure – suppress low frequency vibration under 200Hz for a quicker and more precise position settling.

Adaptive notch filters - 3 sets of notch filters up to 4kHz for better suppression of structural vibration.




### Zero tracking control


Able to realize a zero position deviation during acceleration/ deceleration by improving multi-axis precision and following.



## Part Numbers




## Ports & Connectors



### / Reliable Motion Control Partner


### 400W (AC 220V)

Unit: mm




### 750W/1000W (AC 220V)

### Unit: mm



### 1500W/2000W (AC 220V)


#### Unit: mm



www.leadshine.com 25/26


### 750W/1000W/1.5kW (AC 400V)

Unit: mm




### 2kW/3kW (AC 400V)

Unit: mm




### 4.4kW/5.5kW/7.5kW (AC 400V)

Unit: mm



### **EL7-RS & Peripheral Wiring Diagram**





### • EL7-RS 220V Models

EL7-RSP Series Driver	EL7-RS400P	EL7-RS750P	EL7-RS1000P	EL7-RS1500P	EL7-RS2000P					
Power Rating	400W 750W		1000W	1500W	2000W					
Rated Current (Arms)	3.5	5.5	7.0	9.5	12					
Peak Current (Arms)	9.5	16.6	18.7	31.1	36					
Control circuit power supply	1-Ph AC 200V-240V, -10% - +10%, 50/60Hz									
Main power supply										
Dimension H*L*W(mm)	175*156*40 175*156*50 175*156*80									

### O EL7-RS 400V Models

EL7-RSPT series	EL7- RS750PT	EL7- RS1000PT	EL7- RS1500PT	EL7- RS2000PT	EL7- RS3000PT	EL7- RS4400PT	EL7- RS5500PT	EL7- RS7500PT	
Rated Power(W)	750 1000 1500 2000		2000	3000	4400	5500	7500		
Rated Current (Arms)	2.7	3.5	5.4	8.4	11.9	16.5	20.8	25.7	
Peak Current (Arms)	8.6	10.6	14.9	24.8	33.2	38.9	51.6	33.6	
Control circuit power supply	Three phase AC 380V~440V, -15%~+10%, 50/60Hz								
Main power supply		Single phase AC 380V~440V, -15%~+10%, 50/60Hz							
Dimension L*H*W(mm)	175*179*55 175*179*80 250*230*89								

Ports	Descriptions				
USB Type-C Tuning	Modify or read driver parameters without connecting to main power supply				
Low-speed pulse input	5V differential signal, 0-500kHz 24V single ended signal, 0-200kHz				
High-speed pulse input	5V differential signal, 0-4MHz				
	5V differential signal, 0-4MHz				
High-speed pulse input	3 analog inputs (AI1/AI2/AI3) ,-10V~+10V, Max. voltage: ±12V				
Crossover Frequency Output	Supports phase A/B/Z differential crossover frequency output Supports phase Z open collector crossover frequency output				
Analog I/O	2 analog inputs (AI1/AI2) ,-10V~+10V, Max. voltage: ±12V				
Analog I/O	1 analog output (AO1) , -10V~+10V				
Digital I/O	8 Digital Inputs (Supports common anode or cathode connection) DI1~DI8				
	5 digital outputs (double-ended) DO1~DO5				
Communication Port RS485 communication, Modbus RTU protocol (RJ45 port)					

### / Reliable Motion Control Partner

Control Mode									
Control	1. External pulse train position control 2. JOG control 3. Velocity control 4. Torque control 5. Hybrid control: Position–Torque/Position–Velocity/Velocity–Torque								
	Control Features								
Drive Mode	IGBT SVPWM sinusoidal wave drive								
Encoder feedback	Encoder: RS485 Protocol								
Easy-to-use	One-click tuning, Single parameter tuning, Black box, Zero tracking control								
Notch Filter	Mechanical resonance suppression. Supports up to 3 filters,50Hz~4000Hz								
Vibration suppression	End vibration suppression								
Alarm	Overcurrent. Overvoltage. Undervoltage. Overheat. Overload. Overtravel. Single-Phasing.  Regenerative resistor error. Position deviation error.  Encoder feedback error. Excessive braking rate. EEPROM error								
Front Panel	5 push buttons, 8-segments display								
Software	Driver tuning through Motion Studio Ver. 2.x.								
Dynamic Brake	Internal dynamic brake								
Black Box	Set triggering conditions and analyze the data from black box. Used for error solving								
	Environmental requirements								
Temperature	Storage: -20-80°C (Condensation free); Not < 72 hours if stored in over 65°C Installation: 0-55°C (Not frozen); Lower performance at over 45°C								
Humidity	Under 90%RH (Condensation free)								
Altitude	Max. altitude of 2000m; 100% performance at 1000m or below. Performance decreases by 1% with every increase of 100m from 1000m.								
Vibration	Less than 0.5G (4.9m/s2) 10-60Hz (non-continuous working)								
IP ratings	IP20								

www.leadshine.com | 29/30

# Leadshine









Shanghai Intelligent Industry Park

• Production base in Shenzhen

- Founded in 1997
- Public Listed Company in China (002979.SZ)
- Dedication in Motion Control
   Stepper/Servo systems, Motion Controllers, PLC
   Control systems, I/O Modules, Encoders
- A leading supplier of motion control products and solutions in the world
- Customer Oriented, Technology Oriented, Forever Improving, Sharing of Success


















## **Leadshine Motion Control Total Product System**




## **Leadshine Servo Product**


### **Servo Drive Series**



### Typical Applications




### **Servo Motor Series**



**Application Complexity** 

### Simple Introduction



## **Leadshine Servo Products Quick Selection**

Servo Drive		Power	Voltage	Dimensions (mm)	Weight	Command Source		Co	Command Source			Encoder	Brake	Digital	Digital	Analogue	Analogue	Matched
	Model	(W)	(VAC)		(kg)	Pulse+Dir	Analog Input	RS485	EtherCAT	CANopen	STO		Output	Inputs (Points)	Outputs (Points)	Input	Output	Servo Motors
AC Servo Drive EL8 Series	EL8-EC400F	400		150*150*43	1						$\sqrt{}$	√		8	3	2	2	
	EL8-RS400F	400		130 130 43	ı				√		$\sqrt{}$	√	√	10	6	3	2	
	EL8-EC750F	750	1 Phase/ 3 Phase 220		1.2	√	√	√					√	8	3	2	2	
	EL8-RS750F	750		150*160*55		√	√	√	√		$\sqrt{}$	√	√	10	6	3	2	
	EL8-EC1000F	1000									$\sqrt{}$	√	√	8	3	2	2	
	EL8-RS1000F	1000				√	√	√	√		$\sqrt{}$	√	√	10	6	3	2	
	EL8-EC1500F	1500									$\sqrt{}$	√		8	3	2	2	
	EL8-RS1500F	1500		183*160*80	2	√	√		√		$\sqrt{}$	√	√	10	6	3	2	
	EL8-EC2000F	2000		103.100.00	2						$\sqrt{}$	√	√	8	3	2	2	
	EL8-RS2000F	2000				√	√	√	√		$\sqrt{}$	√	√	10	6	3	2	
	EL7-RS400P	400		175*156*40	0.9	√	√	√				√		8	5	2	1	
AC Servo Drive	EL7-RS750P	750	1 Phase 220	175*156*50	1.1	√	√	√				√		8	5	2	1	
EL7 Series -	EL7-RS1000P	1000			1.2	√	√	√				√		8	5	2	1	ELM1 and ELM2 Servo Motors Please refer to page 84 to 87 for more information on matching servo motors
220VAC	EL7-RS1500P	1500	1 Phase/	175*156*80	2.3	√	√	√				√		8	5	2	1	
	EL7-RS2000P	2000	3 Phase 220	173 130 00	2.3	√	√	√				√		8	5	2	1	
	EL7-RS750PT	750		179*175*55	1.3	√	√	√				√		8	5	2	1	
	EL7-RS1000PT	1000				√	√	√				√		8	5	2	1	
	EL7-RS1500PT	1500				√	√	√				√		8	5	2	1	
AC Servo Drive EL7 Series -	EL7-RS2000PT	2000	3 Phase 400	179*175*80	1.9	√	√	√				√		8	5	2	1	
400VAC	EL7-RS3000PT	3000	0111000 100	177 170 00		√	√	√				√		8	5	2	1	
	EL7-RS4400PT	4400		230*250*90	3.3	√	√	√				√		8	5	2	1	
	EL7-RS5500PT	5500				√	√	√				√		8	5	2	1	
	EL7-RS7500PT	7500				√	√	√				√		8	5	2	1	
	EL7-EC400N	400		175*156*40	0.9				√		√	√		4	3			
AC Servo Drive	EL7-EC750N	750	1 Phase 220	175*156*50	1.2				√		√	√		4	3			
EL7 Series - 220VAC	EL7-EC1000N	1000							√		√	√		4	3			
220VAC	EL7-EC1500N	1500	1 Phase/	179*175*55	2.3				√		√	√		4	3			
	EL7-EC2000N	2000	3 Phase 220						√		$\sqrt{}$	√		4	3			
	EL7-EC750NT	750							√		√	√		4	3			
	EL7-EC1000NT	1000		179*175*55	1.3				√ .		√	√		4	3			
AC Servo Drive	EL7-EC1500NT	1500		179*175*80					√		√	√		4	3			
EL7 Series -	EL7-EC2000NT	2000	3 Phase 400		1.9				√		√	√		4	3			
400VAC	EL7-EC3000NT	3000							√		√	√		4	3			
	EL7-EC4400NT	4400		000+050-5	2.2				√		√ 	√		4	3			
	EL7-EC5500NT	5500		230*250*90	3.3				√ 		√ 	√		4	3			
	EL7-EC7500NT	7500				r			√		√ 	√ 		4	3			
	EL6-RS400P	400		175*156*40	0.9	√		√			√	√		8	5			
	EL6-CAN400Z		1 Phase 220		<b>U.</b> ,					√				4	3			
AC Servo Drive	EL6-RS750P	750		175*156*50	1.1	√		√			√	√		8	5			
EL6 Series	EL6-CAN750Z	, 55		173 130 30	1.1					√				4	3			
	EL6-RS1000P	1000		175*156*50	1.2	√		√			$\sqrt{}$	√		8	5			
	EL6-CAN1000Z	. 500								√				4	3			

## Applications

### **CNC Router**



### **Product Advantages:**

- High torque servo motor with 3 times overloading capability
- 23-bit encoders with great impact resistant and harsh environment resistance
- Servo drive optimized for CNC router applications
- Comes with safety features such as Safe Torque Off and Dynamic Braking
- Servo Motors maximum torque ranging from 0.105Nm up to 119Nm

### **Fiber Laser Cutting**



### **Product Advantages:**

- Great Compatibility with renowned laser cutting controller from FScut, Weihong, Beckhoff, Empower, etc.
- Available with most mainstream communication protocols (EtherCAT, Modbus RTU, PROFINET)
- Accurate positioning of 0.02mm and precision up to 0.01mm
- Easy servo tuning features to assist users in setting up the servo systems
- Robust and compact servo motors with high dust- and waterproof ratings




### **Wafer Cutting**

- Full Closed Loop Control function to realize high accuracy control and real time compensation for lead screw wear.
- Real time control using EtherCAT/PROFINET servo drives.
- Easy-to-use, low maintenance and high reliability.



### **Automated Battery Lamination**

- Linear Motors, Direct Drive Motors and Rotary Servo Motors are available.
- Production cycle time per part as low as 0.55s.
- High accuracy and precision motion control with servo drive frequency response of 3.5kHz



### **Semiconductor Wafer Cleaning**

- High following capability with servo frequency response up to 3.5kHz
- Easy servo tuning features for notch filter settings and anti-vibration tunings
- Industrial Ethernet Standard with communication rate up to 100Mbps and compatible with any mainstream PLCs.